## Section 1: Pairing/Connecting the Samsung Smart Remote to your TV

- 1. <u>Before pairing</u> your remote, <u>charge it to full using the USB-C port</u> on the bottom of the remote (See Section 2 for instructions). *Note: Solar charging cannot be used for initial charging or when the battery is completely empty.*
- 2. Start with the TV powered off. Using your new remote, power the TV on. NOTE: Only the power button will work before being paired.
- 3. With the TV powered ON, point the remote towards the TV then <u>press and hold</u> the buttons simultaneously and <u>DO NOT RELEASE</u> them until pairing is totally complete (step 5).



4. The Bluetooth Icon Should display on your TV screen, which means your TV has begun pairing with your remote.

5. When paired properly, the Pairing Complete Check Mark will appear, showing that your remote is now paired to your TV. You can now release the buttons, and your remote should work as intended.

## Section 2: How to charge the solar remote (Typically takes 2-3 hours from empty battery)

*Note: If the battery is low, your remote control may not function properly, or may respond slowly. Also, Solar charging cannot be used for initial charging or when the battery is completely empty.* 

**Step 1.** Connect the included USB-C cable to the port on the bottom of the remote control.

**Step 2.** Connect the cable to a usb port either on the back of your TV (near the HDMI ports) or any usb slot in your computer. If you have a power brick with a usb-port, this option will work as well.

**Step 3.** The red LED on the front of the remote control will turn on once charging starts and will turn off when charging is complete.



